

Mischverstärker UMA 7120



Flexibler 120 W ELA- Mischverstärker mit praxisorientierter Vollausstattung für vielseitige Einsatzmöglichkeiten vor allem bei kleinen aber anspruchsvollen Beschallungssystemen. Kompakte 2 HE Ausführung.

- 120 W/100-70 V oder 4 Ω
- Eingangskanäle: 4 x Mic, 3 x Aux
- RJ45-Anschluss für Sprechstelle
- Separate Klangregelung pro Kanal
- 48 V-Phantomspeisung
- Mute All-Funktion über potentialfreien Kontakt
- Hochwertiger 2- u. 4-Klang Gong
- DIN Alarmton
- 24 V Notstrombetrieb
- Mikrofon-Prioritätsfunktion
- Pre Out/Main In
- Frontanschlüsse für Mic & Line
- Inkl. 19" Winkeln
- Abmessungen ohne 19" Winkel 88 x 430 x 303 mm (HxBxT)
- Gewicht 12,1 kg

Very flexible and fully fledged 120 W/100 V Mixing Amp with practice orientated features and versatile capabilities. Especially designed with small but demanding systems in mind.

Compact size (2 RU).

- 120 W/100-70 V or 4 Ω
- Input channels: 4 x Mic, 3 x Aux
- RJ45 connector for paging station
- Hi/Lo controls channel
- 48 V-Phantom power
- Mute All-Function by dry contact
- 2 and 4 tone chime with high quality module
- DIN Alarm tone
- 24 V DC operation
- Mic priority function
- Pre Out/Main In
- Front connectors for Mic & Line
- Incl. 19" mounts
- Dimensions without 19" mounts 88 x 430 x 303 mm (HxWxD)
- Weight 12,1 kg



UNielectronic

Mischverstärker UMA 7120



Technische Daten:

Specifications:

Eingänge: Inputs:

MIC 1 - 4 (XLR), 2,5mV / 2kOhm
CD/Tuner/Line (RCA), 350mV / 10kOhm

Ausgänge: Outputs:

Speaker out (plug-in terminal), 100V, 70V, 4 Ohm / 120W
Rec Out (RCA), 775mV / 600 Ohm
Master Out (XLR), 775mV / 600 Ohm

Rauschabstand: S/N ratio:

Mic 1 - 4, > 50dB
CD/Tuner/Line, > 60dB

Klangsteller: Tone controls:

Bass, +/- 10dB at 100 Hz
Treble, +/-10dB at 10kHz

Alarm / Gong: Alarm / Chime:

4- / 2-Tone, DIN Alarm

Stromaufnahme: Power consumption:

24V DC, 8A
230V / 50 Hz, 200VA

Abmessungen (HxBxT): Dimensions (HxWxD):

88 x 430 x 303 mm ohne 19" Winkel
88 x 430 x 303 mm without 19" mounts

Gewicht: Weight:

10 Kg

Zubehör: Accessory:

Paging Station UPM 8001

